

IG3300WP

INDUSTRIAL RANGE
POWER BY WEICHAI

IGNT



POWER DEFINITION

PRP: Prime Power is required for continuous operation under variable load and infinite operating hours per year.

ESP: Standby power refers to the ability of the generator to operate at varying loads in the event of power outage, with an annual operating time of up to 200h.

STANDARD USAGE CONDITIONS:

1. Altitude: below 1000 meters;
2. Environmental temperature: 25 °C
3. Relative humidity: 30%

ABOUT NOISE:

The noise level of the generator largely depends on the installation conditions and usage environment, so it is not possible to specify the noise value in manual. The noise value we provide is based on laboratory testing and is for reference.

QUALIFICATION STANDARD

IGNT POWER generator set complies with ISO and CE standards, which also include the following certification standards:
ISO 1400:2015 Environmental System;
ISO 45001:2018 Safety System;
ISO 9001:2015 Quality System

	SERVICE	PRP	ESP
Power	KVA	3000	3300
Power	KW	2400	2640
Standard Voltage	V	400/230	
Available Voltage	v	380/220	415/240
Rated Current	A	4330	
Frequency/Speed	HZ/RPM	50/1500	

Weight and Dimension

	Dimension	Open	Silent
Length	(L) mm	6500	12192
Width	(W) mm	2850	2438
Height	(H) mm	3290	2591
Net Weight	KG		
Fuel Tank	L		

IG3300WP

INDUSTRIAL RANGE
POWER BY WEICHAI

IGNT

Engine Specifications

General Engine Data -- WEICHAI	
Engine Model	16M55D2900E310
Governer	ECU
Aspiration	Turbocharged & intercooling
No. of Cylinders	16
Displacement (L)	87.5
Bore* Stroke (mm)	180*215
Compression Ratio	16.5
Rated Net Power (KW)	2420
Fuel system	Electronically controlled high pressure common rail

Aspiration system		
Max inlet pressure	kPa	≤3
Combustion volume	L/s	/
Air flow	L/s	12450

Lubrication System		
Oil capacity	L	350
Oil consumption	g/kwh	0.4
Oil pressure	kPa	400-650

Alternator Specifications

Alternator Date-- IGNT	
Alternator Model	TCU528C
Phase	3
Voltage (V)	400
Prime Power (KW)	2400
Pole	4
Excitation System	If-excited, Brushless
No. of Bearing	1
Power Factor	0.8
Wiring Connection	3 Phases, 4 Wires
Insulation Grade	H/H
Protection Grade	IP23
Voltage Regulation (%)	±0.5

Fuel System		
Fuel Consumption @100% ESP	L/h	/
Fuel Consumption @100% PRP	L/h	553
Fuel Consumption @75% PRP	L/h	/
Fuel Consumption @50% PRP	L/h	/
Fuel Tank Capacity	L	4500
Fuel Tank Capacity (Silent)	L	/

Starter System		
Start Motor Voltage	V	24
No. of Batteries		2

Cooling System		
Total coolant capacity	L	89.2
Thermostat operation range	°C	44-56
Coolant alarm temperature	°C	103

Exhaust system		
Exhaust gas flow	L/s	12962
Max. exhaust temperature	°C	720
Max. allowed back pressure	kPa	5

Alternator Date-- Stamford		
Alternator Model		N/A
Phase		3
Voltage	V	400
Prime Power	KW	2400
Pole		4
Excitation System		elf-excited, Brushless
No. of Bearing		3
Power Factor		0.8
Wiring Connection		3 Phases, 4 Wires
Insulation Grade		H/H
Protection Grade		IP23
Voltage Regulation	%	±0.5

Controller Specifications

Control Panel Date-- Deepsea DSE6120

- | | |
|--|--|
| ● Built in PLC logic programming | ● Generator/load current monitoring and protection |
| ○ Generator voltage detection | ○ Fuel pump control function |
| ● Mains voltage detection | ● Can connect to all expansion modules |
| ○ Generator/load power detection (kW, kVA, kVAr, pf) | ○ Capable of graded loading |
| ● Generator overload protection (kW) | ● Engine speed protection |
| ○ Equipped with manual closing and opening functions | ○ Engine preheating |
| ● Start gen-set when the battery voltage is low | ● Engine starts rapidly&stops rapidly |
| ○ LCD and LED alarm indication | ○ Custom remote start signal |

Generator Specifications

Standard Configuration

- 50°C radiator for belt driven fan
- 12/24V charging alternator
- One set of air/fuel/oil filters
- Chassis with integrated fuel tank
- Emergency stop button
- Anti-vibration shock absorbers
- Main circuit breaker/ MCCB
- Auto control system
- User manual

Optional Configuration

- Battery charger
- Engine pre-heater
- Alternator pre-heater
- PMG/ AREP/ MAUX
- Water-oil separator
- Inside automatic transfer switch/ ATS box
- Grounding copper rod
- Remote control system
- Switch box

Warranty of Generator Set

Cummins Engine

One year or 1000 running hours whichever comes first

Generator

One year or 1000 running hours whichever comes first

Email: ignt@igntpower.com

Web: www.igntpower.com