

IG1128P

INDUSTRIAL RANGE
POWER BY PERKINS

IGNT



POWER DEFINITION

PRP: Prime Power is required for continuous operation under variable load and infinite operating hours per year.

ESP: Standby power refers to the ability of the generator to operate at varying loads in the event of power outage, with an annual operating time of up to 200h.

STANDARD USAGE CONDITIONS:

1. Altitude: below 1000 meters;
2. Environmental temperature: 25 °C
3. Relative humidity: 30%

ABOUT NOISE:

The noise level of the generator largely depends on the installation conditions and usage environment, so it is not possible to specify the noise value in manual. The noise value we provide is based on laboratory testing and is for reference.

QUALIFICATION STANDARD

IGNT POWER generator set complies with ISO and CE standards, which also include the following certification standards:
ISO 1400:2015 Environmental System;
ISO 45001:2018 Safety System;
ISO 9001:2015 Quality System

	SERVICE	PRP	ESP
Power	KVA	1025	1128
Power	KW	820	902
Standard Voltage	V	400/230	
Available Voltage	v	380/220	415/240
Rated Current	A	1480	
Frequency/Speed	HZ/RPM	50/1500	

Weight and Dimension

	Dimension	Open	Silent
Length	(L) mm	4700	6096
Width	(W) mm	2150	2438
Height	(H) mm	2250	1592
Net Weight	KG		
Fuel Tank	L		

IG1128P

INDUSTRIAL RANGE
POWER BY PERKINS

IGNT

Engine Specifications

General Engine Data -- PERKINS	
Engine Model	4008TAG2
Governor	E
Aspiration	Turbocharged
No. of Cylinders	8
Displacement (L)	30.5
Bore* Stroke (mm)	160*190
Compression Ratio	13
Rated Net Power (KW)	800
Cooling system	Water-cooled

Air inlet system

Mounted air filter and turbocharger

Lubrication System

Wet full aluminium sump with filler and dipstick
Full flow spin-on oil filters

Alternator Specifications

Alternator Data -- IGNT	
Alternator Model	IA634E
Phase	3
Voltage (V)	400
Prime Power (KW)	800
Pole	4
Excitation System	If-excited, Brushless
No. of Bearing	1
Power Factor	0.8
Wiring Connection	3 Phases, 4 Wires
Insulation Grade	H/H
Protection Grade	IP23
Voltage Regulation (%)	±0.5

Fuel System		
Fuel Consumption @100% ESP	L/h	234
Fuel Consumption @100% PRP	L/h	213
Fuel Consumption @75% PRP	L/h	160
Fuel Consumption @50% PRP	L/h	108
Fuel Tank Capacity (Open)	L	
Fuel Tank Capacity (Silent)	L	

Starter System

Start Motor Voltage	V	24
No. of Batteries		2

Cooling System

Cooling system Triple thermostats
System designed for ambient temperatures of up to 50° c

Alternator Data -- Stamford		
Alternator Model		S6L1D-E4
Phase		3
Voltage	V	400
Prime Power	KW	800
Pole		4
Excitation System		Self-excited, Brushless
No. of Bearing		3
Power Factor		0.8
Wiring Connection		3 Phases, 4 Wires
Insulation Grade		H/H
Protection Grade		IP23
Voltage Regulation	%	±0.5

Controller Specifications

Control Panel Date-- Deepsea DSE6120

- | | |
|--|--|
| ● Built in PLC logic programming | ● Generator/load current monitoring and protection |
| ● Generator voltage detection | ● Fuel pump control function |
| ● Mains voltage detection | ● Can connect to all expansion modules |
| ● Generator/load power detection (kW, kVA, kVAR, pf) | ● Capable of graded loading |
| ● Generator overload protection (kW) | ● Engine speed protection |
| ● Equipped with manual closing and opening functions | ● Engine preheating |
| ● Start gen-set when the battery voltage is low | ● Engine starts rapidly&stops rapidly |
| ● LCD and LED alarm indication | ● Custom remote start signal |

Generator Specifications

Standard Configuration

- 50°C radiator for belt driven fan
- 12/24V charging alternator
- One set of air/fuel/oil filters
- Chassis with integrated fuel tank
- Emergency stop button
- Anti-vibration shock absorbers
- Main circuit breaker/ MCCB
- Auto control system
- User manual

Optional Configuration

- Battery charger
- Engine pre-heater
- Alternator pre-heater
- PMG/ AREP/ MAUX
- Water-oil separator
- Inside automatic transfer switch/ ATS box
- Grounding copper rod
- Remote control system
- Switch box

Warranty of Generator Set

Cummins Engine

One year or 1000 running hours whichever comes first

Generator

One year or 1000 running hours whichever comes first

Email: ignt@igntpower.com

Web: www.igntpower.com