

IG50P

INDUSTRIAL RANGE
POWER BY PERKINS

IGNT



POWER DEFINITION

PRP: Prime Power is required for continuous operation under variable load and infinite operating hours per year.

ESP: Standby power refers to the ability of the generator to operate at varying loads in the event of power outage, with an annual operating time of up to 200h.

STANDARD USAGE CONDITIONS:

1. Altitude: below 1000 meters;
2. Environmental temperature: 25 °C
3. Relative humidity: 30%

ABOUT NOISE:

The noise level of the generator largely depends on the installation conditions and usage environment, so it is not possible to specify the noise value in manual. The noise value we provide is based on laboratory testing and is for reference.

QUALIFICATION STANDARD

IGNT POWER generator set complies with ISO and CE standards, which also include the following certification standards:
ISO 1400:2015 Environmental System;
ISO 45001:2018 Safety System;
ISO 9001:2015 Quality System

SERVICE		PRP	ESP
Power	KVA	45	50
Power	KW	36	40
Standard Voltage	V	400/230	
Available Voltage	v	380/220	415/240
Rated Current	A	65	
Frequency/Speed	HZ/RPM	50/1500	

Weight and Dimension

	Dimension		Open	Silent
Length	(L)	mm	1700	2390
Width	(W)	mm	750	1000
Height	(H)	mm	1190	1450
Net Weight		KG		
Fuel Tank		L		166

IG50P

INDUSTRIAL RANGE
POWER BY PERKINS

IGNT

Engine Specifications

General Engine Data -- PERKINS	
Engine Model	1103A-33TG1
Governer	M
Aspiration	Turbocharged
No. of Cylinders	3
Displacement (L)	3.3
Bore* Stroke (mm)	105*127
Compression Ratio	17.25
Rated Net Power(KW)	36
Cooling system	Water-cooled

Air intake system	
Intake air flow	L/s 48.3

Lubrication System	
Min. capacity	L 6.2
Max. oil temperature permitted in oil pan	°C 125

Alternator Specifications

Alternator Date-- IGNT	
Alternator Model	IA224D
Phase	3
Voltage (V)	400
Prime Power (KW)	40
Pole	4
Excitation System	If-excited, Brushless
No. of Bearing	1
Power Factor	0.8
Wiring Connection	3 Phases, 4 Wires
Insulation Grade	H/H
Protection Grade	IP23
Voltage Regulation (%)	±0.5

Fuel System	
Fuel Consumption @110% PSP	L/h 12
Fuel Consumption @100% PRP	L/h 10.7
Fuel Consumption @75% PRP	L/h 8.2
Fuel Consumption @50% PRP	L/h 5.7
Fuel Tank Capacity (Open)	L
Fuel Tank Capacity (Silent)	L 166

Starter System	
Start Motor Voltage	V 12
No. of Batteries	1

Cooling System	
Coolant capacity-engine only	L 3.6
Thermostat adjusting temperatur	°C 82-93
Min. Pressure Cap	kPa 90

Exhaust system	
Max.exhaust temperature	°C 492
Exhaust gas flow	L/s 116
Max.allowed back pressure	kPa 10

Alternator Date-- Stamford	
Alternator Model	SOL2-R1
Phase	3
Voltage V	400
Prime Power KW	40
Pole	4
Excitation System	Self-excited, Brushless
No. of Bearing	3
Power Factor	0.8
Wiring Connection	3 Phases, 4 Wires
Insulation Grade	H/H
Protection Grade	IP23
Voltage Regulation %	±0.5

Controller Specifications

Control Panel Date-- Deepsea DSE6120

- | | |
|--|--|
| ● Built in PLC logic programming | ● Generator/load current monitoring and protection |
| ● Generator voltage detection | ● Fuel pump control function |
| ● Mains voltage detection | ● Can connect to all expansion modules |
| ● Generator/load power detection (kW, kVA, kVAR, pf) | ● Capable of graded loading |
| ● Generator overload protection (kW) | ● Engine speed protection |
| ● Equipped with manual closing and opening functions | ● Engine preheating |
| ● Start gen-set when the battery voltage is low | ● Engine starts rapidly&stops rapidly |
| ● LCD and LED alarm indication | ● Custom remote start signal |

Generator Specifications

Standard Configuration

- 50°C radiator for belt driven fan
- 12/24V charging alternator
- One set of air/fuel/oil filters
- Chassis with integrated fuel tank
- Emergency stop button
- Anti-vibration shock absorbers
- Main circuit breaker/ MCCB
- Auto control system
- User manual

Optional Configuration

- Battery charger
- Engine pre-heater
- Alternator pre-heater
- PMG/ AREP/ MAUX
- Water-oil separator
- Inside automatic transfer switch/ ATS box
- Grounding copper rod
- Remote control system
- Switch box

Warranty of Generator Set

Cummins Engine

One year or 1000 running hours whichever comes first

Generator

One year or 1000 running hours whichever comes first

Email: ignt@igntpower.com

Web: www.igntpower.com